

Energy Matters

122 Bank Street South Melbourne

Victoria, 3205 Australia

Phone: 03 9697 1900 Fax: + 61 3 9682 6322

<http://www.energymatters.com.au/>

5.5 Hp - 12 Volt 120 Amp High Powered Battery Charger

Specifications:

Weight	26kg
Dimensions (mm):	510L x 385W x 380H
Engine:	Honda GX160 air cooled
Alternator:	Bosch 120 amp
Max eng. power:	5.5hp @ 3600rpm.
Fuel capacity:	3.6 Litres
Fuel consumption:	Approx. ¾ Litres / hour
Fuel type:	4 stroke Unleaded petrol
Oil capacity:	0.6 Litres
Starting system:	Recoil or electric
Electric output:	12 Volts D.C.
Max voltage (low):	14 Volts regulated
Max voltage (high):	14.8 Volts regulated
Max amp output:	120 Amps
Voltage cut out:	18 Volts
Charge indication:	10mm LED



This larger model is best suited for larger charging requirements, such as the marine industry, backup for solar powered sites, motor-homes, earthmoving contractors, emergency services, mobile mechanics, communication repeaters, arrow boards, council machinery etc. Designed for the harsh environments of Australia, so no digital electronic components are installed on this model.

**24-volt@45-amp model also available with the 5.5hp Honda engine.
ELECTRIC START AVAILABLE**

PROUDLY MADE IN AUSTRALIA

Features include:

- Environmentally friendly Honda 5.5hp 4-stroke engine.
- Low or high charge rate, by the flick of a switch.
- Short circuit and over voltage protected.
- Super bright LED charge indication light.
- Lightweight, weighing only 22 kg.
- 3m long heavy-duty high current leads & alligator clamps.

Ideal uses:

- Farmers can supply enough charge in as little as 5 minutes to start machinery.
- Run car fridges for 24 hours and charge your batteries in as little as 1 hour.
- 12 Volt lighting or other appliances can be powered in emergency situations.

Note, some deep cycle batteries will not accept a fast charge & may require trickle charging for a long period of time.

