

Energy Matters

122 Bank Street South Melbourne

Victoria, 3205 Australia

Phone: 03 9697 1900 Fax: + 61 3 9682 6322

<http://www.energymatters.com.au/>

3Hp - 80 Amp High Powered Outback Battery Charger

Specifications:

Weight	22kg
Dimensions (mm):	465L x 330W x 450H
Engine:	Honda GX100 air cooled
Alternator:	Bosch 80 amp
Max eng. power:	3hp@3600rpm
Fuel capacity:	1.2 Litres
Fuel type:	4-stroke unleaded petrol
Fuel consumption:	Approx. ¼ Litres / hour
Oil capacity:	0.4 Litres
Starting system:	Recoil
Electric output:	12 Volts D.C.
Max voltage (low):	14 Volts regulated
Max voltage (high):	14.8 Volts regulated
Max amp output:	80 Amps
Voltage cut out:	18 Volts



PROUDLY MADE IN AUSTRALIA

Features include:

- Environmentally friendly OHC Honda 100cc 4-stroke engine.
- Low or high charge rate, by the flick of a switch.
- Short circuit and over voltage protected.
- Super bright LED charge indicator.
- Lightweight, portable, weighing only 22 kg.
- High current Leads included, 3m long with heavy-duty alligator clamps.



Ideal uses:

- Ideal for charging up to 2- N70 cranking batteries at once.
- Farmers can supply enough charge in as little as 5 minutes to start any machinery.
- Run car fridges for 24 hours and charge your batteries in as little as 1 hour.
- 12 Volt lighting or other appliances can be powered in emergency situations.
- Ideal for the marine industry, backup for solar powered sites, emergency services, earthmoving contractors, mobile mechanics, or anyone working in the outback.
- Note, some deep cycle batteries will not accept a fast charge & may require trickle charging for a long period of time.